

Product Highlights

High-Speed Networking

Enjoy lightning-fast, Gigabit connectivity to your PC or Mac, with any available USB Type-C port on your computer

Ideal for Ultra-Thin Laptops

Add a wired Ethernet connection to laptops without an Ethernet port to enjoy a consistent high-speed network connection

No Installation Needed

Simply connect to an available USB Type-C port to enjoy gigabit connectivity in seconds; no further installation necessary



DUB-E130

USB-C to Gigabit Ethernet Adapter

Features

Gigabit Connectivity

- Achieve transfer speeds of up to 1 Gbps
- Status LEDs for connection status and data transfer speed
- Auto 10/100/1000 Mbps speed detection with auto-negotiation to always use the highest available speed

USB Type-C 3.0 with Simple Installation

- Simply plug-in and you're ready to go
- No additional hardware or software installation required
- Small and compact design makes it easy to take with you wherever you go

Dynamic Power Management

- Reduces power consumption during times of light traffic, when idle, or when the Ethernet cable is unplugged
- Supports the built-in power-saving features of the USB Type-C 3.0 standard
- Designed for use with ultraportable computers

The DUB-E130 USB-C to Gigabit Ethernet Adapter allows you to instantly add Gigabit connectivity to your ultraportable laptop computer. Just plug the DUB-E130 into an available USB type-C port and you're ready to connect to your switch, or router with the speed and reliability of a wired Gigabit connection.

Gigabit Ethernet Connectivity

The DUB-E130 USB-C to Gigabit Ethernet Adapter plugs into any available USB Type-C port on your computer to enable you to connect to an Ethernet network at speeds up to 1 Gbps for up to ten times faster transfer speeds compared to previous standards. High-speed Gigabit Ethernet allows you to transfer large files in no time, or make light work of backups to a server or network storage device. Especially where wireless connectivity is inconsistent or unavailable, this adaptor allows you to connect seamlessly.

Easy to Install and Use

The DUB-E130 USB-C to Gigabit Ethernet Adapter connects to your computer's USB Type-C port and is ready to run as soon as it's plugged in. Plug-and-Play¹ design ensures that there is no need to change any configuration settings or install any software on your computer. For extra convenience, the adapter's compact design means you can easily slip the DUB-E130 into your pocket or laptop bag and take it with you.

Wake-on-LAN

If your computer supports Wake-On-LAN function, the DUB-E130 can be used to resume your computer from standby or be powered on via LAN. If you plan on accessing your computer remotely for any reason this feature allows you to retain access to your files and programs while keeping the computer in a low-power state to save energy.

DUB-E130 USB-C to Gigabit Ethernet Adapter

Energy-saving Functionality

Power to the DUB-E130 is provided directly by the USB Type-C port, eliminating the need for an external AC power adapter. The DUB-E130 not only supports the USB 3.0 standard's power-saving features, but also includes an energy-saving suspend and resume function to minimise power consumption when network traffic is light, the device is idle, or when the Ethernet cable is unplugged. This feature is especially useful in helping to conserve battery life, allowing you to keep working for longer without needing to recharge.

Hardware Overview



Technical Specifications

Connectivity

Device Interfaces	<ul style="list-style-type: none"> • RJ-45 Ethernet Port (10/100/1000 Mbps) 	<ul style="list-style-type: none"> • USB Type-C Connector
LEDs	<ul style="list-style-type: none"> • Speed (orange) 	<ul style="list-style-type: none"> • Link/ACT (green)
Standards	<ul style="list-style-type: none"> • USB Specification Version 3.0 • USB Specification Version 2.0 • USB Specification Version 1.1 • OHCI (Open Host Controller Interface) • EHCI (Enhanced Host Controller Interface) 	<ul style="list-style-type: none"> • IEEE 802.3 Ethernet • IEEE 802.3u Fast Ethernet • IEEE 802.3ab Gigabit Ethernet • Supports suspended mode and remote wakeup • Supports full duplex in Gigabit Ethernet mode • Wake-On-LAN support

General

Minimum System Requirements	<ul style="list-style-type: none"> • Microsoft Windows 10/8/7/Vista/XP 	<ul style="list-style-type: none"> • Mac OS 10.6 or above
Power Management	<ul style="list-style-type: none"> • Advanced Power Management reduces power usage during idle or light traffic periods 	

Physical

Dimensions (including plug and cable)	<ul style="list-style-type: none"> • 205 x 26.5 x 15 mm (8.07 x 1.04 x 0.59 in) 	
Weight	<ul style="list-style-type: none"> • 28 g (1.0 oz.) 	
Power	<ul style="list-style-type: none"> • Input: Bus-powered 500 mA, 5 V DC 	<ul style="list-style-type: none"> • Consumption: 176 mA, 5 V DC
Temperature	<ul style="list-style-type: none"> • Operating: 0 to 40° C (32 to 104 °F) 	<ul style="list-style-type: none"> • Storage: -20 to 70 °C (-4 to 158 °F)
Humidity	<ul style="list-style-type: none"> • Operating: 20% to 80% RH, non-condensing 	<ul style="list-style-type: none"> • Storage: 5% to 90% RH, non-condensing
Certifications	<ul style="list-style-type: none"> • CE 	<ul style="list-style-type: none"> • FCC

¹ Windows 8/10 and Mac OS 10.11.6 or above operating systems support plug-and-play functionality. Other operating systems may require software installation before the product can be used. Recent versions of Windows require users to confirm before automatic installation can begin.



For more information: www.dlink.com

D-Link European Headquarters. D-Link (Europe) Ltd., First Floor, Artemis Building, Odyssey Business Park, West End Road, South Ruislip HA4 6QE, United Kingdom. Specifications are subject to change without notice. D-Link is a registered trademark of D-Link Corporation and its overseas subsidiaries. All other trademarks belong to their respective owners. ©2018 D-Link Corporation. All rights reserved. E&OE.

Updated December 2018

D-Link®